Product sheet



ARTEOR[™] WITH NETATMO LEGRAND

Arteor[™] with Netatmo - Starter pack for a connected installation

REF. 574209 | EAN. 3414971352926

> Visit e-catalogue

Product characteristics

- Gateway power outlet : Measures instantaneous and total electricity consumption. Protects against overloads, breaking at 16 A maximum. Compatible with any electrical appliance or large household appliance. LED indicator with locator function which can be activated in the app. Wi
 Fi 2.4 GHz 802.11 b/g/n
- Home/Away wireless master switch : Predefined Home/Away scenarios which can be customised from the Home + Control app. Supplied with a replaceable battery with an 8 - year life. LED indicator with low battery warning
- Connected power outlet (Schuko standard) : LED indicator with locator function which can be activated in the app. Compatible with any electrical appliance or large household appliance. Measures instantaneous and total electricity consumption. Protects against overloads (16 A maximum)
- White

Recommendation / Restriction

• A Wi-Fi connection viayour router is required.

Documentation

TECHNICAL DOCUMENTATION

- → LE11046AA.pdf | PDF (8.08Mo)
- **F02616EN-00.pdf** | PDF (0.62Mo)

Agreements & Certificates

- Decl. UE RED-A 3812 B | (0.25Mo)
- E OC / CB-FR_707098 | (0.67Mo)

The product's benefits

Installation

• The Arteor with Netatmo gateway power outlet is easily installed in place of an existing standard power outlet and needs a standard-depthflush-mounting box (40 mm). Claw or screw fixing possible.

Usage

 Voice control of your lights and electrical appliances via a voice assistant

CATALOGUE PAGE & OTHERS

ex223001_0606.pdf | PDF (0.1Mo)