

# Product sheet



ARTEOR™ WITH NETATMO LEGRAND

Arteor™ with Netatmo - Starter pack for a connected installation

REF. 574218 | EAN. 3414971353084

> [Visit e-catalogue](#)

## Product characteristics

- Gateway power outlet : Measures instantaneous and total electricity consumption. Protects against overloads, breaking at 16 A maximum. Compatible with any electrical appliance or large household appliance. LED indicator with locator function which can be activated in the app. Wi - Fi 2.4 GHz 802.11 b/g/n
- Home/Away wireless master switch : Predefined Home/Away scenarios which can be customised from the Home + Control app. Supplied with a replaceable battery with an 8 - year life. LED indicator with low battery warning
- Connected power outlet (Schuko standard) : LED indicator with locator function which can be activated in the app. Compatible with any electrical appliance or large household appliance. Measures instantaneous and total electricity consumption. Protects against overloads (16 A maximum)
- Alu

## Recommendation / Restriction

- A Wi-Fi connection via your router is required.

## Documentation

### TECHNICAL DOCUMENTATION

→ LE11046AA.pdf | PDF (8.08Mo)

F02616EN-00.pdf | PDF (0.62Mo)

### Agreements & Certificates

Decl. UE RED-A 3812 B | (0.25Mo)

OC / CB-FR\_707098 | (0.67Mo)

## The product's benefits

### Installation

- The Arteor with Netatmo gateway power outlet is easily installed in place of an existing standard power outlet and needs a standard-depth flush-mounting box (40 mm). Claw or screw fixing possible.

### Usage

- Voice control of your lights and electrical appliances via a voice assistant

### CATALOGUE PAGE & OTHERS

ex223001\_0606.pdf | PDF (0.1Mo)