

CAT. N° 4 121 64

**SINGLE PHASE SPLIT CORE CT - FOR 80 X 120 MM BAR -
TRANSF RATIO 1000/5**

Pack (number of units)	1
Volume (dm ³)	2,356
Weight (g)	1 414,00

Product characteristics**Single-phase split-core current transformers**

- Used with ammeters, electricity meters or multi-function measuring units
- Current at the secondary: 5 A
- For fixing directly on bars
- Secondary connected by terminals or lugs
- Precision class: 0,5 %

For 80 x 120 mm bar

- Transformation ratio : 1000/5
- Output : 5 VA

General characteristics**Current transformers (CT)****Documentation** **Catalogue pages & additional information**

- [Description page \(p.106\)](#)
- [Current transformers \(CT\)](#)

 **Installation & technical data**

- [F01961EN-02](#)